ISRA (India) **= 4.971** ISI (Dubai, UAE) = 0.829

GIF (Australia) = 0.564= 1.500

РИНЦ (Russia) = **0.126 = 8.997** ESJI (KZ) **SJIF** (Morocco) = **5.667**

= 0.912

QR - Issue

SIS (USA)

ICV (Poland) PIF (India) IBI (India)

= 6.630= 1.940= 4.260

QR - Article

OAJI (USA) = 0.350

SOI: 1.1/TAS DOI: 10.15863/TAS International Scientific Journal

Theoretical & Applied Science

p-ISSN: 2308-4944 (print) **e-ISSN:** 2409-0085 (online)

Year: 2020 Issue: 06 Volume: 86

http://T-Science.org Published: 30.06.2020





Denis Chemezov

Vladimir Industrial College M.Sc.Eng., Corresponding Member of International Academy of Theoretical and Applied Sciences, Lecturer, Russian Federation https://orcid.org/0000-0002-2747-552X vic-science@yandex.ru

Vladimir Goremykin

Vladimir Industrial College Master of Industrial Training, Russian Federation

Alexey Kuzin

Vladimir Industrial College Student, Russian Federation

Alexandr Petrenko

Vladimir Industrial College Master of Industrial Training, Russian Federation

Emil Akhmetov

Vladimir Industrial College Student, Russian Federation

Irina Pavlukhina

Vladimir Industrial College Lecturer, Russian Federation

Irina Medvedeva

Vladimir Industrial College Master of Industrial Training, Russian Federation

Mikhail Ustinov

Vladimir Industrial College Student, Russian Federation

Sergey Markov

Vladimir Industrial College Student, Russian Federation

TO THE QUESTION OF ELECTRICAL DISCHARGE MACHINING OF THE STEEL WORKPIECE WITH THE STEEL ELECTRODE

Abstract: The impact of electric discharge on the processed surface of the steel workpiece in the conditions of electrical discharge machining with the steel cylindrical electrode was considered in the article. The electrical and thermal parameters of electrical discharge machining were calculated for the pulse duration of 0.5 s. The depth of the deformed layer of the workpiece material is presented in the three-dimensional view.



ISRA (India)	= 4.971	SIS (USA)	= 0.912	ICV (Poland)	= 6.630
ISI (Dubai, UAE	(2) = 0.829	РИНЦ (Russ	ia) = 0.126	PIF (India)	= 1.940
GIF (Australia)	= 0.564	ESJI (KZ)	= 8.997	IBI (India)	= 4.260
JIF	= 1.500	SJIF (Moroco	co) = 5.667	OAJI (USA)	= 0.350

Key words: the electrode, the workpiece, electrical discharge machining, the ring, the deformed layer.

Language: English

Citation: Chemezov, D., et al. (2020). To the question of electrical discharge machining of the steel workpiece with the steel electrode. *ISJ Theoretical & Applied Science*, 06 (86), 545-550.

Soi: http://s-o-i.org/1.1/TAS-06-86-100 Doi: https://dx.doi.org/10.15863/TAS.2020.06.86.100

Scopus ASCC: 2209.

Introduction

Electrical discharge machining (EDM) is the progressive type of processing of various conductive materials. EDM can be carried out both with electrodes (for forming the blind profile) and with wire (for cutting the through profile). The low performance and the low-forecast tool wear are the main disadvantages of EDM. Some researches of the effective implementation of EDM are presented in the works [1-10].

Electric discharge that causes local heating of processed material passes between the surfaces of the tool and the workpiece in the process of EDM. The temperature increases intensively on the surface layers and leads to melting of the workpiece material in the short period of time. Thus, EDM includes the combination of thermomechanical, hydrodynamic,

electrical and other processes. The presentation of intensity of volumetric deformation of the workpiece material will allow to choose the rational modes for roughing or finishing EDM. Let us consider thermal deformation and changing the volume of the workpiece material during EDM with the steel electrode.

Materials and methods

The passing process of discharge current between the surfaces of the electrode (the tool) and the workpiece was modeled according to the condition of the computer experiment. The electrode was the solid cylinder. The workpiece was the solid disk. The electrode and the workpiece were made of structural steel. The models for the computer experiment are presented in the Fig. 1.




Figure 1 – The models for the experiment: A – The orientation and the models dimensions of the tool and the workpiece; B – The detail section that explains the size of the spark gap.

EDM was carried out in the gas environment. Electric discharge of 10000~mA and duration of 0.5~s occurred in the spark gap. Voltage during EDM was accepted 25000~mV.

The size of the finite element indicates the accuracy of the computer calculation. The three-

dimensional models of the tool and the workpiece after splitting into the finite elements are shown in the Fig. 2. The size of one element was accepted 1.5 mm. The mesh on the workpiece model was denser, which increased the accuracy of the simulation results in the processing zone.



ISRA (India) **= 4.971** ISI (Dubai, UAE) = 0.829**GIF** (Australia) = 0.564JIF = 1.500

SIS (USA) = 0.912**РИНЦ** (Russia) = **0.126** ESJI (KZ) **= 8.997 SJIF** (Morocco) = **5.667**

ICV (Poland) = 6.630PIF (India) = 1.940IBI (India)

OAJI (USA)

= 4.260 = 0.350




Figure 2 – The view of the models after splitting into the finite elements.

Calculation

The main part of the calculation of EDM is presented in the generated report.

***** ANSYS SOLUTION ROUTINE *****

USE A MAXIMUM OF 1 EQUILIBRIUM ITERATIONS EACH SUBSTEP

*** WARNING *** CP = 5.195

Using 1 iteration per substep may result in unconverged solutions for nonlinear analysis and the program may not indicate divergence in this case. Check your results.

DO NOT USE PREDICTOR METHOD FOR ALL DEGREES OF FREEDOM

SPECIFIED CONSTRAINT VOLT PICKED NODES

REAL = LOADVARI62 IMAG = 0.000000000

ALL SELECT FOR ITEM = NODE COMPONENT =

IN RANGE 1 TO 80428 STEP 1

80428 NODES (OF 80428 DEFINED) SELECTED BY NSEL COMMAND

SELECT COMPONENT CM33

*GET NODNUM FROM NODE ITEM = NUM MIN VALUE = 1483.00000

SPECIFIED NODAL LOAD AMPS FOR SELECTED NODES 1483 TO 1483 BY 1 REAL = LOADVARI33 IMAG = 0.000000000

COUPLED SET = 1 DIRECTION = VOLT $TOTAL\ NODES = 224$

MAXIMUM COUPLED SET NUMBER = 1

ALL SELECT FOR ITEM = NODE COMPONENT =

IN RANGE 1 TO 80428 STEP 1

80428 NODES (OF 80428 DEFINED) SELECTED BY NSEL COMMAND

*** WARNING *** CP = 5.257

Element shape checking is currently inactive. Issue SHPP, ON or SHPP, WARN to reactivate, if desired.

*** WARNING *** CP = 5.413

Material number 4 (used by element 18190) should normally have at least one MP or one TB type command associated with it. Output of energy by material may not be available.

*** NOTE *** CP = 5.444

This nonlinear analysis defaults to using the full Newton-Raphson solution procedure. This can be modified using the NROPT command.

The conditions for direct assembly have been met. No .emat or .erot files will be produced.

It is highly recommended to use the solution control option by issuing the SOLCONTROL, ON command for this problem for robustness and efficiency.

*** NOTE *** CP = 6.131

It is highly recommended to use the auto contact setting option by issuing CNCHECK, AUTO command for this problem in order to achieve better convergence.

*** NOTE *** CP = 6.131

Symmetric deformable-deformable contact pair identified by real constant set 3 and contact element type 3 has been set up. The companion pair has real constant set ID 4. Both pairs should have the same behavior.

ANSYS will keep the current pair and deactivate its companion pair, resulting in asymmetric contact.

Electrostatic contact is activated.



ISRA (India) **= 4.971** SIS (USA) = 0.912ICV (Poland) = 6.630**РИНЦ** (Russia) = **0.126** ISI (Dubai, UAE) = 0.829PIF (India) = 1.940**GIF** (Australia) = 0.564IBI (India) = 4.260 ESJI (KZ) **= 8.997** = 0.350JIF = 1.500**SJIF** (Morocco) = **5.667** OAJI (USA)

Contact detection at: Gauss integration point Average contact surface length 1176.9 Average contact pair depth 1481.5 Default pinball region factor PINB 0.25000 The resulting pinball region 370.37 Initial penetration/gap is excluded. Bonded contact (always) is defined. Electric contact capacitance coef. ECC

Electric contact capacitance coef. ECC 0.65574E+12

*** NOTE *** CP = 6.131

Min. initial gap 200 was detected between contact element 18261 and target element 18764.

The gap is closed due to initial settings.

*** WARNING *** CP = 6.131

The geometric gap/penetration may be too large. Increase pinball radius if it is a true geometric gap/penetration. Decrease pinball if it is a false one.

*** NOTE *** CP = 6.131

Symmetric deformable-deformable contact pair identified by real constant set 4 and contact element type 3 has been set up. The companion pair has real constant set ID 3. Both pairs should have the same behavior.

ANSYS will deactivate the current pair and keep its companion pair, resulting in asymmetric contact.

Electrostatic contact is activated.

Contact detection at: Gauss integration point

Average contact surface length 747.17

Average contact pair depth 1500.0

Default pinball region factor PINB 0.25000

The resulting pinball region 375.01

Initial penetration/gap is excluded.

Bonded contact (always) is defined.

Electric contact capacitance coef. ECC 0.65574E+12

*** NOTE *** CP = 6.131

Min. initial gap 200 was detected between contact element 18328 and target element 18248.

The gap is closed due to initial settings.

SUMMARY FOR CONTACT PAIR IDENTIFIED BY REAL CONSTANT SET 3

Max. penetration of -7.275957614E-12 has been detected between contact element 18276 and target element 18733.

Max. geometrical gap of 200 has been detected between contact element 18258 and target element 18681.

*** WARNING *** CP = 9.173

Contacting area 78538884.

Max. pinball distance 370.370007.

One of the contact searching regions contains at least 22 target elements.

SUMMARY FOR CONTACT PAIR IDENTIFIED BY REAL CONSTANT SET 4

*** NOTE *** CP = 9.173

Contact pair is inactive.

Range of element maximum matrix coefficients in global coordinates

Maximum = 2.943955282E+17 at element 18311.

Minimum = 7.605535165E+15 at element 513.

*** ELEMENT MATRIX FORMULATION TIMES

TYPE NUMBER ENAME TOTAL CP AVE CP

1 1809 SOLID231 0.468 0.000259

2 16380 SOLID231 3.822 0.000233

3 413 CONTA174 0.094 0.000227

4 413 TARGE170 0.031 0.000076

Time at end of element matrix formulation CP = 9.2040596.

CURRENT CONVERGENCE VALUE = 0.1702E+20 CRITERION = 0.1702E+17

SPARSE MATRIX DIRECT SOLVER.

Number of equations = 75192, Maximum wavefront = 551

*** NOTE *** CP = 13.806

Sparse solver maximum pivot 5.855352997E+17 at node 1483 VOLT.

Sparse solver minimum pivot = 4.283506717E+15 at node 25678 VOLT.

Sparse solver minimum pivot in absolute value = 4.283506717E+15 at node 25678 VOLT.

*** ELEMENT RESULT CALCULATION TIMES

TYPE NUMBER ENAME TOTAL CP AVE CP

1 1809 SOLID231 0.312 0.000172

2 16380 SOLID231 2.480 0.000151

3 413 CONTA174 0.062 0.000151

4 413 TARGE170 0.031 0.000076

FINISH SOLUTION PROCESSING

Results and discussion

The simulation results are presented by the color contours of the total electric field intensity, the total current density, Joule heat and the volume on the workpiece model (the Fig. 3). The total electric field intensity and the total current density have the same distribution in the volume of the workpiece model. In the central part of the processed area of the workpiece, intensity of these electrical parameters is less than in



ISRA (India) **= 4.971** SIS (USA) = 0.912ICV (Poland) = 6.630**РИНЦ** (Russia) = **0.126** ISI (Dubai, UAE) = 0.829PIF (India) = 1.940= 8.997 = 4.260 **GIF** (Australia) = 0.564ESJI (KZ) IBI (India) = 0.350JIF = 1.500**SJIF** (Morocco) = **5.667** OAJI (USA)

the peripheral part. Maximum intensity is expressed by the contour ring.

During EDM, the heat source is partly surface in nature, partly formed by Joule heat released inside of the workpiece. Joule heat is defined as the product of the electric field intensity and the current density. Significant heat generation will occur on the periphery of the processed surface. Heat is released unevenly in the area of the contour ring.

The depth of the deformed layer of the workpiece is presented in the Fig. 3, C. The deformed

volume of the workpiece material has the sphere shape. The maximum diameter of the deformed workpiece material equal to 1.5d of the electrode, the maximum depth equal to 0.4d of the electrode (d is the electrode diameter, mm).

The workpiece volume increases in the direction from the center to the periphery at destruction of the surface layers of material. The volume increases up to 8 times. At the same time, the volume practically does not change in the most deformed material of the workpiece.




Figure 3 – The simulation results: A – The total electric field intensity and the total current density; B – Joule heat; C – The depth of the deformed layer of the workpiece; D – The volume.

Conclusion

EDM with the steel cylindrical electrode is accompanied by the formation of the peak heat ring, which is located on the periphery of the deformation

area of the steel workpiece. The depth of deformation (destruction) of material increases from the periphery to the center of the processed surface layer of the workpiece.

Authors





ISRA (India) **= 4.971** SIS (USA) = 0.912ICV (Poland) = 6.630**РИНЦ** (Russia) = **0.126** PIF (India) ISI (Dubai, UAE) = 0.829= 1.940= 4.260 **GIF** (Australia) = 0.564ESJI (KZ) = 8.997 IBI (India) = 0.350**JIF** = 1.500**SJIF** (Morocco) = **5.667** OAJI (USA)

References:

- 1. Orlov, Yu., et al. (2019). Influence of processing modes on wear resistance of copper and graphite electrodes. *International Journal of Innovation Engineering and Science Research*, volume 3, issue 2, 1-13.
- 2. Pawade, M. M., & Banwait, S. S. (2013). A Brief Review of Die Sinking Electrical Discharging Machining Process towards Automation. *American Journal of Mechanical Engineering*, 1(2), 43-49.
- 3. Wong, Y. S., Lim, L. C., & Lee, L. C. (1995). Effects of Flushing on Electro-Discharge Machined Surfaces. *Journal of Materials Processing Technology*, 48, 299-305.
- 4. McGeough, J. A. (1988). Electro discharge machining in Advanced Methods of Machining. *Chapman & Hall, London*, pp. 130.
- 5. Kiyak, M., & Cakir, O. (2007). Examination of machining parameters on surface roughness in EDM of tool steel. *Journal of Materials Processing Technology*, 191, 141-144.

- 6. Ramarao, P. V., & Faruqi, M. A. (1982). Characteristics of the surfaces obtained in electro-discharge machining. *Precision Engineering*, 4/2, 111-113.
- 7. Lee, H. T. (1996). Influence of EDM process parameters on surface defects and roughness. *Chin. J. Mater. Sci.*, 28/4, 270-278.
- 8. Halkaci, H. S., & Erden, A. (2002). Experimental investigation of surface roughness in electric discharge machining. 6th Biennial Conference (ESDA 2002), Turkey, 1-6.
- 9. Cogun, C., Kocabas, B., & Ozgedik, A. (2004). Experimental and theoretical investigation of workpiece surface roughness profile in EDM. *J. Fac. Engg. Arch.*, *19*, 97-106.
- 10. Chemezov, D., et al. (2019). Stability analysis of electrical discharge machining with brass wire. *ISJ Theoretical & Applied Science*, 11 (79), 101-104.

