

Impact Factor:

ISRA (India) = 6.317
ISI (Dubai, UAE) = 1.582
GIF (Australia) = 0.564
JIF = 1.500

SIS (USA) = 0.912
ПИИИ (Russia) = 3.939
ESJI (KZ) = 8.771
SJIF (Morocco) = 7.184

ICV (Poland) = 6.630
PIF (India) = 1.940
IBI (India) = 4.260
OAJI (USA) = 0.350

SOI: [1.1/TAS](#) DOI: [10.15863/TAS](#)

International Scientific Journal Theoretical & Applied Science

p-ISSN: 2308-4944 (print) e-ISSN: 2409-0085 (online)

Year: 2022 Issue: 04 Volume: 108

Published: 16.04.2022 <http://T-Science.org>

Issue

Article



Vadim Andreevich Kozhevnikov

Peter the Great St. Petersburg Polytechnic University
Senior Lecturer
vadim.kozhevnikov@gmail.com

Alexander Prokopevich Ammosov

Peter the Great St. Petersburg Polytechnic University
Student
ammosovlex@gmail.com

IMPROVED COMPREHENSIVE METHOD OF CALCULATING OUTPUT POWER OF HE-NE LASERS

Abstract: In this paper, an improved method for estimating the He-Ne laser radiation power is compared with experimental data, which takes into consideration the dependence of the population inversion on the laser axis on the transverse dimensions of the active element. The numerical calculations results correspond to the experimental data.

Key words: effective mode volume, population inversion, He-Ne laser power, tube geometry.

Language: English

Citation: Kozhevnikov, V. A., & Ammosov, A. P. (2022). Improved comprehensive method of calculating output power of He-Ne lasers. *ISJ Theoretical & Applied Science*, 04 (108), 354-357.

Soi: <http://s-o-i.org/1.1/TAS-04-108-44> **Doi:**  <https://dx.doi.org/10.15863/TAS.2022.04.108.44>

Scopus ASCC:

Introduction

This paper continues the cycle of papers devoted to the dependence of the energy characteristics of the He-Ne laser on the geometry of its active element [1-14]. In these articles, a method was proposed for estimating the radiation power of a He-Ne laser with an arbitrary geometric shape of the active element. Namely, it is proposed to be considered by the formula

$$P = \int_{NMV} \varepsilon E^2 \delta N dV \quad (1)$$

where E is the modulus of electric field strength in the resonator, δN is the population inversion and the integration occurs in the effective mode volume NMV . NMV is defined as a body bounded by the surface, where the $E^2 \delta N$ value falls in e^2 times compared to $E_0^2 \delta N_0$ (where δN_0 is the δN value at the axis, and e is the natural logarithm base). The emission power of a laser with circle, rectangular and elliptical cross sections of the active element with different transverse dimensions has been calculated, assuming the same δN_0 . However, with the further development of the model, assumptions were made about the influence of the transverse dimensions of the tube on the value δN_0 .

In [14], this problem was investigated, and it was shown that indeed, δN_0 should decrease with an increase in the transverse size of the active element. In this paper, we compare the results of calculations of the power of a He-Ne laser with active elements in the form of cylindrical tubes of different radii with experimental data from classical works.

Population inversion and He-Ne laser output power

First, let us recall the main results obtained earlier. In [12], the processes in the discharge positive column (PC) in laser tubes of smoothly varying diameter were investigated, and a system of equations was obtained that solves the problem of coupling external, controlled parameters of the PC (radius of the discharge channel $R(z)$, gas inlet pressure p_H , and discharge current I_p) with its main internal characteristics: the electron temperature T_e , the concentration of charged particles n , longitudinal electric field strength E_z . There was also obtained such an expression for the electron concentration as a

Impact Factor:

ISRA (India) = 6.317
 ISI (Dubai, UAE) = 1.582
 GIF (Australia) = 0.564
 JIF = 1.500

SIS (USA) = 0.912
 ПИИИ (Russia) = 3.939
 ESJI (KZ) = 8.771
 SJIF (Morocco) = 7.184

ICV (Poland) = 6.630
 PIF (India) = 1.940
 IBI (India) = 4.260
 OAJI (USA) = 0.350

function of the radial r and longitudinal z coordinates:
 $n_e = n_e(r, z)$:

$$n_e(r, z) = \frac{J_0(r\mu_1^{(0)} / R_z) \cdot 0,737I_p}{R_0^2 f_R^2(z) e b_e E_{0z} f_{E_z}(z)} \quad (2)$$

where J_0 – zero-order Bessel function, $\mu_1^{(0)} \approx 2.4048$ – its first root, $R(z) \equiv R_z = R_0 f_R(z)$ – is the discharge channel radius as a function of the longitudinal coordinate z ($0 < z < l$), directed along the discharge tube axis ($R_0 = R(0)$ – is the channel radius value at $z=0 \Rightarrow f_R(0)=1$), I_p – is the discharge current, e – elementary charge, b_e electron mobility. In equation (2) \mathbf{E}_z – the longitudinal electric field has the form $\mathbf{E}_z = E_{0z} f_{E_z}(z)$ (where $E_{0z} = E_z(0)$, $f_{E_z}(0)=1$) and it is from the equation:

$$(eE_z)^2(z) = 3kT_e(z) \frac{m_e v_{ea}(z)}{m_a} \{m_e v_{ea}(z) + \frac{4}{R(z)^2 v_{ia}} \left[eU_i + kT_e(z) \left(1,7 + \ln 0,4 \sqrt{\frac{m_i}{m_e}} \right) \right] \} \quad (3)$$

where m_a , m_i , m_e – are the masses of atoms, ions, and electrons respectively, v_{ea} and v_{ia} – are the frequencies of electron-atomic and ion-atomic collisions, U_i – atom ionization potential. In turn, the electron temperature T_e in (3), which is a function of the longitudinal coordinate ($T_e = T_e(z)$), can be found from the equation:

$$\sqrt{\frac{\varepsilon_i}{kT_e(z)}} \cdot \exp\left(\frac{\varepsilon_i}{kT_e(z)}\right) / \left(1 + \frac{\varepsilon_i}{2kT_e(z)}\right) = 0,552 \frac{e}{\sqrt{m_e}} \left(\frac{C_i \sqrt{\varepsilon_i}}{b_i n_a}\right) n_a^2 R_0^2 f_R^2(z) \quad (4)$$

where ε_i – is the ionization energy, k – is Boltzmann's constant, b_i – is the ions mobility, n_a – is a concentration of atoms, C_i – is a constant of approximation of the direct ionization cross section $\sigma_{0i}(\varepsilon_e)$ dependence on the electron's energy ε by the linear dependence: $\sigma_{0i} = C_i(\varepsilon_e - \varepsilon_i)$ at $\varepsilon_e \geq \varepsilon_i$.

Knowing the electron concentration, it is possible to estimate the metastable helium atoms concentration and excited neon atoms, and then population inversion δN . Using the values of the PC parameters in the work [14] it was shown that the population inversion δN_0 on the axis of the cylindrical tube decreases with increasing tube radius a .

In this regard, the method of calculating the He-Ne laser power is refined considering the dependence

$\delta N_0(a)$. For a laser with a cylindrical active element, the radiation power will be according to the formula:

$$P = \int_0^{2\pi} \int_{z_1}^{z_2} \int_0^{\rho(z)} \varepsilon E^2 \delta N_0 \rho dz r dr = \frac{4\pi E_0^2 \varepsilon R_e}{k} \int_{z_1}^{z_2} dz \delta N_0(a) \left(\frac{1 - \exp(-2\rho^2(z) / w^2(z))}{4} - \frac{\mu_1^{(0)2}}{32a^2} (w^2(z) - (w^2(z) + 2\rho^2(z)) \cdot \exp(-2\rho^2(z) / w^2(z))) + \frac{\mu_1^{(0)4}}{512a^4} (w^4(z) - (w^4(z) + 2w^2(z)\rho^2(z) + 2\rho^4(z)) \cdot \exp(-2\rho^2(z) / w^2(z))) \right) \quad (5)$$

where R_e is the radius of curvature of the corresponding equivalent confocal resonator: $R_e = \{4S(R_1 - S)\}^{1/2}$, $S = d(R_2 - d)/(R_1 + R_2 - 2d)$, R_1 and R_2 – radii of mirrors, d – distance between mirrors, z_1 and z_2 – coordinates specifying the position of the tube inside the optical resonator ($z_2 - z_1 = l$ – tube length), z it is counted from the Gaussian beam waist, E_0 – the value of the field on the axis at $z=0$, $k = 2\pi/\lambda$ – wavenumber, $w(z) = \sqrt{(R_e + 4z^2 / R_e) / k}$, $\mu_1^{(0)} = 2.4048$ – is the first solution of the zero-order Bessel function J_0 , a – is the radius of the tube, $\rho(z)$ – solution equation

$$\{2 + \ln 2 - \ln(w^2(z)k / R_e) - 2r^2 / w^2(z) + \ln(J_0(\mu_1^{(0)} r / a))\} |_{r=\rho} = 0$$

and the dependence $\delta N_0(a)$ is taken from the paper [14].

The purpose of this paper was to compare the calculations of the He-Ne laser radiation power according to the refined formula (5) with experimental data for cylindrical tubes of different radius a .

Calculation and comparison with experiment

We have taken experimental data from well-known classical fundamental works on He-Ne laser [15-19]. The calculation results according to formula (5) and experimental data are shown in Figure 1. Here, the radiation power (calculated P_{teor} and experimental P_{exp}) is deposited along the ordinate axis, and the laser number from the experiments is deposited along the abscissa axis. The laser parameters are given in Table 1.

The parameters of the corresponding lasers are given in Table 1.

Table 1. Laser parameters

Laser number	1	2	3	4	5
Work	[15]	[15]	[16]	[17]	[18]
l , m	0.125	0.55	0.11	0.22	0.45
a , mm	0.75	1.5	1.5	0.75	0.775
d , m	0.22	0.7	0.25	0.34	1.3

Impact Factor:

SISRA (India) = 6.317	SIS (USA) = 0.912	ICV (Poland) = 6.630
ISI (Dubai, UAE) = 1.582	ПИИИ (Russia) = 3.939	PIF (India) = 1.940
GIF (Australia) = 0.564	ESJI (KZ) = 8.771	IBI (India) = 4.260
JIF = 1.500	SJIF (Morocco) = 7.184	OAJI (USA) = 0.350

R_1, m	0.5	2	3	2	1.5
R_2, m	∞	∞	10	2	1.5
Laser number	6	7	8	9	10
Work	[19]	[19]	[19]	[19]	[19]
l, m	0.11	0.11	0.11	0.11	0.11
a, mm	0.3	0.4	0.5	0.3	0.4
d, m	0.135	0.135	0.135	0.135	0.135
R_1, m	0.4	0.4	0.4	0.8	0.8
R_2, m	0.4	0.4	0.4	0.8	0.8
Laser number	11	12	13	14	15
Work	[19]	[19]	[19]	[19]	[19]
l, m	0.11	0.38	0.38	0.38	0.38
a, mm	0.5	0.75	1.0	1.25	1.5
d, m	0.135	0.45	0.45	0.45	0.45
R_1, m	0.8	1.265	1.265	1.265	1.265
R_2, m	0.8	1.265	1.265	1.265	1.265
Laser number	16	17			
Work	[19]	[19]			
l, m	0.38	1.195			
a, mm	1.75	1.75			
d, m	0.45	1.265			
R_1, m	1.265	3.572			
R_2, m	1.265	3.572			




Fig 1. Comparison of calculated P_{teor} power values with experimental P_{exp} values for 17 lasers

Conclusion

The results of the evaluation of the He-Ne laser output power for the case of an active element in the form of a cylindrical tube according to уточненному методу are in good agreement with experimental data.

This once again proves the correctness of this method. Currently, the positive discharge column model is becoming more complicated for the case of a polyatomic gas, which will further refine our model.

References:

Impact Factor:

ISRA (India) = 6.317
ISI (Dubai, UAE) = 1.582
GIF (Australia) = 0.564
JIF = 1.500

SIS (USA) = 0.912
ПИИИ (Russia) = 3.939
ESJI (KZ) = 8.771
SJIF (Morocco) = 7.184

ICV (Poland) = 6.630
PIF (India) = 1.940
IBI (India) = 4.260
OAJI (USA) = 0.350

1. Kozhevnikov, V.A., & Privalov, V.E. (2018). The geometrical effect of an active element cross-section on the laser gain. *St. Petersburg Polytechnical State University Journal. Physics and Mathematics*, V. 11 No. 2, pp. 77 – 87. DOI: 10.18721/JPM.11208
2. Kozhevnikov, V.A., & Privalov, V.E. (2018). Radiation Amplification in Lasers with Regular Polygon Cross Sections. *Russian Physics Journal*, V. 61 No. 5, pp.913-917. DOI: 10.1007/s11182-018-1477-4
3. Kozhevnikov, V.A., & Privalov, V.E. (2019). Investigations of Nonconventional Cross Sections of Gas-Discharge Lasers. *Russian Physics Journal*, V. 61 No. 10, pp. 1861-1867, 2019. DOI: 10.1007/s11182-019-01610-5
4. Kozhevnikov, V.A., Privalov, V.E., & Shemanin, V.G. (2019). Gas laser energy characteristics with different active element cross section geometry. *Journal of Physics: Conference Series*, 1236, pp. 012027, 2019. DOI:10.1088/1742-6596/1236/1/012027
5. Kozhevnikov, V.A., Privalov, V.E., & Shemanin, V.G. (2019). Upgrade the Evaluation of the Contribution of the Active Element Cross Section Geometry to the He-Ne Laser Energy Characteristics. *Optical Memory and Neural Networks*, V. 28 No. 3, pp. 215–221, 2019. DOI: 10.3103/S1060992X19030056
6. Kozhevnikov, V.A., & Privalov, V.E. (2020). Gain of a He-Ne Laser with an Active Element Cross-section in the Form of a Hyperbolic Polygon. Proceedings of the 2020 IEEE International Conference on Electrical Engineering and Photonics (EExPolytech), St. Petersburg, Russia, pp. 261-264. DOI: 10.1109/EExPolytech50912.2020.9243964
7. Kozhevnikov, V.A., & Privalov, V.E. (2021). Laser Gain for Inhomogeneous Boundary Conditions. *Russian Physics Journal*, V. 63 No. 9, pp. 1631-1638. DOI: 10.1007/s11182-021-02215-7
8. Kozhevnikov, V.A., Privalov, V.E., & Shemanin, V.G. (2019). Effective Mode Volume Evolution in the He-Ne Laser. Proceedings of the 2019 IEEE International Conference on Electrical Engineering and Photonics (EExPolytech), pp. 272-274. DOI: 10.1109/EExPolytech.2019.8906832
9. Kozhevnikov, V.A., Privalov, V.E., & Shemanin, V.G. (2020). Radiation Power of He-Ne Laser with Different Geometry of the Tube Cross Section. Springer Proceedings in Physics, V. 255, Proceedings of the YETI 2020, pp. 343-350. DOI: 10.1007/978-3-030-58868-7_39
10. Kozhevnikov, V.A., Privalov, V.E., & Fotiadi, A.E. (2020). The effective mode volume and estimation of helium-neon laser output power. *St. Petersburg Polytechnical State University Journal. Physics and Mathematics*, V. 13 No.4, pp. 88-97, 2020. DOI: 10.18721/JPM.13410
11. Kozhevnikov, V.A., Privalov, V.E., & Fotiadi, A.E. (2021). A new approach to the assessment of the output power for a helium-neon gas laser with different cross-sectional geometry of the active element. *St. Petersburg Polytechnical State University Journal. Physics and Mathematics*. V. 14 No. 3. DOI: 10.18721/JPM.14310
12. Kozhevnikov, V.A., Privalov, V.E., & Fotiadi, A.E. (2019). Positive column of a direct current discharge in laser tubes of variable diameter. *St. Petersburg Polytechnical State University Journal. Physics and Mathematics*, V. 12 No.4, pp. 93–103. DOI: 10.18721/JPM.12410
13. Kozhevnikov, V.A., Privalov, V.E., Fotiadi, A.E., & Shemanin, V.G. (2021). Calculation of Parameters of Positive Column in Laser Tubes of Variable Diameter. Springer Proceedings in Physics, V. 255, Proceedings of the YETI 2020, pp. 335-342. DOI: 10.1007/978-3-030-58868-7_38
14. Kozhevnikov, V.A., Privalov, V.E., Fotiadi, A.E., & Shemanin, V.G. (2021). Effect of the He-Ne laser population inversion dependence on its transverse dimensions on the radiation power. Proceedings of the 2021 IEEE International Conference on Electrical Engineering and Photonics (EExPolytech), St. Petersburg, Russia, 2021, pp. 176-178, DOI: 10.1109/EExPolytech53083.2021.9614930
15. Field Jr., R.L. (1967). Operating Parameters of dc-Excited He-Ne Gas Lasers. *Review of Scientific Instruments*, V. 38 No. 12, pp. 1720-1722, 1967. DOI: 10.1063/1.1720653
16. Hansen, J.W., Rodgers, K.F., & Thomas Jr., D.E. (1968). Amplitude Stabilization of a Single Mode, 6328 Å, He-Ne Laser. *Review of Scientific Instruments*, V. 39 No. 6, pp. 872-877, 1968. DOI: 10.1063/1.1683527
17. Kolb, W.P. (1975). Five-Year Operation of a He-Ne Laser. *IEEE Journal of Quantum Electronics*, V. 11 No. 7, pp. 374–375. DOI: 10.1109/JQE.1975.1068644
18. Rittner, K., Hope, A., & Muller-Wirts, T. (1992). Continuous Anti-Stokes Raman Lasers in a He-Ne Laser Discharge. *IEEE Journal of Quantum Electronics*, V. 28 No. 1, pp. 342- 347, 1992. DOI: 10.1109/3.119533
19. Petru, F., Vesela, Z. (1972). The output power of 633nm He-Ne lasers. *Opto-electronics*, V. 4, pp. 1-20. DOI: 10.1007/BF01418396